

Product Search Data Sheet

Note: This datasheet may be out of date. Please download the latest datasheet of BLM15BX182SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15BX182SN1%23

"#" indicates a package specification code.

BLM15BX182SN1#







< List of part numbers with package codes >

BLM15BX182SN1B

BLM15BX182SN1D

BLM15BX182SN1J



### Appearance & Shape



1.0±0.05







(in mm)



# Packaging Information

			Standard
	Packaging	Specifications	Packing
			Quantity
	В	Bulk(Bag)	1000
	D	180mm Paper Tape	10000
	J	330mm Paper Tape	50000



# **Applications**

Other Usage

For general

1 of 4

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.





# BLM15BX182SN1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM15BX182SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15BX182SN1%23

"#" indicates a package specification code.



### **Features**

connection to ground.

The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.

BLM series is effective in circuits without stable ground lines because BLM series does not need a

The nickel barrier structure of the external electrodes provides excellent solder heat resistance. BLM\_B series generates an impedance from the relatively low frequencies.

BLM\_B series is suitable for advanced high-density mounting, and is followed on a miniaturization of digital equipment,

or module of a functional portion.

Because of newly developed ferrite material, BLM15BX has been realized lower DC resistance and larger rated current than BLM15BD series.

2 of 4

#### Attention

- 1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.
- 2. This datasheet has only typical specifications because there is no space for detailed specifications
- Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering





# BLM15BX182SN1#

Note: This datasheet may be out of date.

Please download the latest datasheet of BLM15BX182SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15BX182SN1%23

"#" indicates a package specification code.



# **Specifications**

Shape	SMD
Size Code (in inch)	0402
Length	1.0mm
Length Tolerance	±0.05mm
Width	0.5mm
Width Tolerance	±0.05mm
Thickness	0.5mm
Thickness Tolerance	±0.05mm
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.001g
Number of Circuit	1
Rated Current (at 85°C)	250mA
Rated Current (at 125°C)	250mA
DC Resistance(max.)	0.9Ω
Impedance (at 100MHz)	1800Ω
Impedance (at 100MHz) Tolerance	±25%
Size Code (in mm)	1005

3 of 4

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.



# BLM15BX182SN1#


Note: This datasheet may be out of date.


Please download the latest datasheet of BLM15BX182SN1# from the official website of Murata Manufacturing Co., Ltd.

http://www.murata.com/en/products/productdetail?partno=BLM15BX182SN1%23

"#" indicates a package specification code.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

4 of 4

### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering.

